

Éääèàòóðú G11 è G15

Ðaçääè : Íóëüòèìääèà.Éãðú.Ðaçääè÷áìèÿ

Ïíóáèèèîââîî [DrStrip](#) [16/05/2010]

Áñòü ó íáÿ èääèàòóðú G11 ïä Win è íáé áñòü ñíðò èìòíðúé ïçáìèÿþúéé íáñððàèääòü áá
ääííèíèòääüíúá G èääèèèè. Ðãøèè ÿ íáñððíèòü G èääèèèè è óíðàáèáíèá Multimedia á Open Suse.

Ïíóáèèèîââîî www.g15tools.com

Ñèà÷àè ñ ñàèòà [G15Tools libraries](#) è [G15Daemon and utilities](#)

Áèääèèòáèè è óèèèèòü á èñòíáíèèáð, ñèääíáàðàèüíí äèÿ óñòáííáèè ïíááíáèèòüñÿ ñðááá äèÿ
èííèèèÿðèè.

Ïðè èííèèèÿðèè ïí ðóáííóèñÿ íà libusb è lib15render áðàè ïòñþàà [libusb homepage](#) è [G15Tools libraries](#)

Ïñèá èííèèèÿðèè è óñòáííáèè á /etc/rc.d/ ñíçääè ñèðèòü äèÿ çàííóèè è ïñòáííáèè ááííá.

```
#!/bin/bash
# Copyright (c) 2008
# All rights reserved
#
# Author:
# /etc/rc.d/g15
#
### BEGIN INIT INFO
# Provides:    g15daemon
# Required-Start:
# Required-Stop:
# Default-Start: 3 5
# Default-Stop: 0 1 2 6
# Description:  Logitech G15 Keyboard daemon
### END INIT INFO

G15_BIN=/usr/sbin/g15daemon
G15_DAEMON_OPTIONS=-d
G15_PID=/var/run/g15daemon.pid

./etc/rc.status
rc_reset

#check for missing binary
# if [ ! -x ${G15_BIN} ];
# then
#   echo -n >&2 "G15 daemon: ${G15_BIN} is not found."
#   rc_status -s
```

```

# exit 3
# fi

start()
{
echo -n "Starting G15daemon..."
# checkproc -p ${G15_PID} ${G15_BIN}
checkproc ${G15_BIN}
if ["$?" == "0"];
then
echo -n "G15 daemon: - Warning! Daemon is already running! Try 'restart' instead 'start' "
exit 2;
fi
# 1) echo -n "G15 daemon: - Warning! ${G15_PID} exist" ;;
#start daemon
startproc -f -p ${G15_PID} ${G15_BIN} ${G15_DAEMON_OPTIONS}
rc_status -v
exit 0
}
#-----
stop()
{
echo -n "Shutting down G15daemon..."
checkproc -p ${G15_PID} ${G15_BIN} ||
echo -n "G15 daemon: - Warning! G15 daemon is not running! "
killproc -p ${G15_PID} -t 2 ${G15_BIN}
rc_status -v
exit 0
}

#check parametr for daemon
case "$1" in
start)
start
;;
stop)
stop
;;
restart|reload)
stop
start
;;
*)
echo -n "Usage: $0 start|stop|restart"
exit 1
;;
esac
rc_exit

```

#EOF

Óñòáíàâèèââáí òðíáíè çàíóñêà ÷áðäç Yast 3 è 5

Çàíóñêàâí ááííí.

Ïðè ìííùè óèèèèòù xev ïðáááäëÿàí êíäú G êèèàèø.

Äëÿ ìÿíèíà ÿ èñííèüçíáàè xmodmap, ñíçääè á äííàøíáé ìàíèá ñêðèò ñ ìáííé êííáíáíé xmodmap

~/.Xmodmaprc, êíòíðúé çàíóñêàâòñÿ ÷áðäç àáòíçàíóñêè KDE.

Â óàèèá .Xmodmaprc ïðííèñáí ìÿíèíá ìàíðèíáð:

keycode 177 = XF86Terminal

keycode 160 = XF86AudioMute

keycode 174 = XF86AudioLowerVolume

keycode 176 = XF86AudioRaiseVolume

keycode 162 = XF86AudioPlay

keycode 164 = XF86AudioStop

keycode 144 = XF86AudioPrev

keycode 153 = XF86AudioNext

keycode 152 = XF86AudioMedia

keycode 190 = XF86WWW

Âñèè ó Âñ èèàâèàòòðà G15 òí äíèæáí ðááííàòòü è àèñíèáé, íí ÿ ýòí íá ïðíááðÿè ò.é. íáò G15 ■