





```
#
# this config file was automatically generated
# using lirc-0.8.6(sb0540) on Wed Jun 2 02:21:43 2010
#
# contributed by
#
# brand:          Creative
# model no. of remote control: RM-1500
# devices being controlled by this remote: Audigy 4
#
```

```
begin remote
```

```
name Creative_RM-1500
bits      16
eps       30
aeps      100
```

```
one       0 0
zero      0 0
pre_data_bits 16
pre_data  0x8322
gap       103967
toggle_bit_mask 0x0
```

```
begin codes
```

```
POWER      0x0000000000000619E # Power
1          0x00000000000008B74 # 1
2          0x00000000000008F70 # 2
3          0x0000000000000906F # 3
4          0x00000000000008A75 # 4
5          0x0000000000000847B # 5
6          0x00000000000007887 # 6
7          0x00000000000008976 # 7
8          0x0000000000000837C # 8
9          0x00000000000007788 # 9
0          0x0000000000000807F # 0
CMSS       0x0000000000000718E # CMSS
EAX        0x00000000000008C73 # EAX
MUTE       0x00000000000006E91 # Mute
VOLUMEDOWN 0x0000000000000639C # Vol_Down
VOLUMEUP   0x0000000000000629D # Vol_Up
UP         0x00000000000007B84 # Up
LEFT       0x00000000000008778 # Left
OK         0x0000000000000817E # Ok
RIGHT      0x0000000000000758A # Right
DOWN       0x00000000000008D72 # Down
RETURN     0x00000000000008E71 # Return
START      0x00000000000008877 # Start
```



end

```
begin
button = MUTE
prog = irexec
config = amixer sset Master mute
config = amixer sset Master unmute
repeat = 0
delay = 0
end
```

```
~/.lirc/tvtime begin
button = POWER
prog = irexec
config = tvtime &
config = tvtime-command QUIT
end
```

```
begin
  prog = irexec
  button = UP
  config = tvtime-command UP
  repeat = 1
end
begin
  prog = irexec
  button = DOWN
  config = tvtime-command DOWN
  repeat = 1
end
```

```
begin
  prog = irexec
  button = DISPLAY
  config = tvtime-command DISPLAY_INFO
  repeat = 1
end
```

```
begin
  prog = irexec
  button = MUTE
  config = tvtime-command TOGGLE_MUTE
end
```

```
begin
```

```
    prog = irexec
    button = 1
    config = tvtime-command CHANNEL_1
end
begin
    prog = irexec
    button = 2
    config = tvtime-command CHANNEL_2
end
begin
    prog = irexec
    button = 3
    config = tvtime-command CHANNEL_3
end
begin
    prog = irexec
    button = 4
    config = tvtime-command CHANNEL_4
end
begin
    prog = irexec
    button = 5
    config = tvtime-command CHANNEL_5
end
begin
    prog = irexec
    button = 6
    config = tvtime-command CHANNEL_6
end
begin
    prog = irexec
    button = 7
    config = tvtime-command CHANNEL_7
end
begin
    prog = irexec
    button = 8
    config = tvtime-command CHANNEL_8
end
begin
    prog = irexec
    button = 9
    config = tvtime-command CHANNEL_9
end
begin
    prog = irexec
    button = 0
    config = tvtime-command CHANNEL_0
end
```

```

begin
  prog = irexec
  button = OK
#  config = tvtime-command ENTER
  config = tvtime-command SHOW_MENU &
  config = tvtime-command ENTER
end
#begin
#  prog = irexec
#  button = OK
#  config = tvtime-command MENU_SHOW
#end

```

```

begin
  prog = irexec
  button = RETURN
  config = tvtime-command CHANNEL_JUMP
  repeat = 1

```

end

Äÿ íðìàëüííé ðàáíòù irexec áâí íàâí ñíà-:àèà çàíòñòèòù èàè äáííí irexec -d è äíáääèòù á àâðíçàãðóçéó íêííííí íáíáäæáðà.

Áìò ñíáñòááííí è äñá.

Óää-è!

İðèíá-:áíèá: Áñèè ó TV-tunera áñòù ííääáðæèà íóèüòà, òí íí (íóèüò) áèèèòñÿ ñèñòáííé, èàè íáú-ííá óñòðíéñòâí áâííàà /dev/input/eventX (ãää X íííáð óñòðíéñòâà). Èàè ñáíáíáðàçíäÿ èèääèèòóðà. cat /proc/bus/input/devices áúáááàò ààí áñá ààøè óñòðíéñòâà input. Äÿ äâí ðàáíòù ííá lírc èñííèüçóéòá äðàéááð devinput, à á èà-:áñòâá óñòðíéñòâà /dev/input/eventX.